

TITLE OF THE INVENTION

RECORDING MEDIUM MANAGEMENT DEVICE AND DIGITAL CAMERA
INCORPORATING SAME

FIELD OF THE INVENTION

5 The present invention relates to recording medium
management devices for managing a recording medium with
cluster units each of which comprises a plurality of
sectors, and digital cameras incorporating the recording
medium management device.

10 BACKGROUND OF THE INVENTION

Generally, when data recording/playback devices such
as digital cameras record image file data, etc. on
recording media including memory cards, the number of
sectors providing one cluster, i.e., cluster size is
15 written in the region referred to as PBR (Partition Boot
Record) of the recording medium, and the recording medium
is managed with use of the two recording units of the
cluster and the sector. The cluster size is set to the
power of 2 of the number of sectors.

20 For the recording medium, the image file data and the
like are arranged for the cluster units. Even though the
data has 1 byte, one cluster is used for the record of the
data. Accordingly, as the cluster size becomes larger, the
more space is wasted. However, as the cluster size becomes

larger, one data file can be recorded with less number of clusters, whereby access speed becomes high.

Accordingly, the cluster size is approximately inversely proportional to the access speed. The larger
5 cluster size makes it possible to realize high-speed access. This wastes, however, more space in recording a small sized file. Conversely, whereas the smaller cluster size decreases wasted space, the access speed is reduced.

However, with the recording/playback devices of
10 portable type such as digital cameras, since the recording medium is formatted for a predetermined cluster size corresponding to the capacity of the recording medium, there arises the problem of not considering the user's request, in the case where the user gives greater priority
15 to high speed in access than recordable capacity of the recording medium, or conversely the user gives greater priority to recordable capacity of the recording medium than high speed in access.

SUMMARY OF THE INVENTION

20 An object of the present invention is to provide a recording medium management device and digital camera wherein formatting can be performed in response to the request of the user, who gives priority to high speed in access to the recording medium, or to the recordable

capacity of the medium.

The recording medium management device of the present invention comprises:

graphical user interface displayer for displaying on a
5 screen a graphical user interface having a first display
portion for inputting priority ratio of high speed in
access to the recording medium to recordable capacity of
the recording medium in formatting the recording medium, a
second display portion for displaying a cluster size
10 representing the number of sectors providing one cluster,
and a third display portion for displaying the number of
data files recordable to the recording medium,

cluster size determiner/displayer for determining the
cluster size in response to the user's inputting
15 manipulation to the first display portion of the graphical
user interface shown on the screen, and displaying the
determined cluster size on the second display portion of
the graphical user interface,

calculator/displayer for calculating the number of data
20 files recordable to the recording medium in response to the
determined cluster size, and displaying the calculated
number of the files on the third display portion of the
graphical user interface, and

formatter for formatting the recording medium with the

cluster size displayed on the second display portion of the graphical user interface in response to the user's determining manipulation.

Furthermore, the digital camera embodying the present invention comprises the recording medium management device of the present invention and a display for showing various items of information.

With the recording medium and the digital camera of the present invention, the screen has shown thereon the graphical user interface in formatting the recording medium. The user manipulates the first display portion to input a desired priority ratio of high-speed in access to recordable capacity, determining the cluster size in response to the input ratio. As the high speed in access is given greater priority, the cluster size is set larger. As the recordable capacity of the medium is given greater priority, the cluster size is set smaller. The set cluster size is shown on the second display portion. Further the number of data files recordable to the recording medium is calculated based on the cluster size, having the calculated number of the files shown on the third display portion.

Accordingly, the user can confirm the cluster size and the number of the recordable data files obtained by the format of the recording medium by referring to the

presentation of the graphical user interface. If the user is content with the cluster size and the number of the files presented, the user performs a determining manipulation. On the other hand, if the user is not
5 content with the cluster size and the number of the files, the user reinputs the priority ratio of high-speed in access to recordable capacity to change the cluster size and the number of recordable files.

When the user performs the determining manipulation,
10 the recording medium is formatted with the cluster size shown at the moment on the second display portion of the graphical user interface.

As described above, the recording medium management device of the present invention and digital camera
15 incorporating same are adapted to perform formatting for satisfying the user's request in high-speed in access and recordable capacity of the recording medium.

BRIEF DESCRIPTION OF THE DRAWINGS

FIG. 1 is a block diagram showing a structure of a
20 digital camera embodying the present invention;

FIG. 2 is a flow chart showing a procedure for setting the format of an external memory card of the digital camera of the present invention;

FIG. 3 is a flow chart showing a speed-oriented

setting procedure;

FIG. 4 is a flow chart showing a capacity-oriented setting procedure;

FIG. 5 is a flow chart showing data recording operation of the digital camera;

FIG. 6(a), (b), (c) are diagrams exemplifying graphical user interfaces shown on a display of the digital camera of the present invention, respectively.

DETAILED DESCRIPTION OF EMBODIMENT

10 An embodiment of the invention as applied to a digital camera will be described below in detail with reference to the drawings. As shown in FIG. 1, a digital camera 1 of the present invention comprises a CCD 2 for picking up images, a signal processor 3 for giving a predetermined
15 signal processing to image data obtained by the CCD 2, a CPU 4, image compression processor 5 for compressing the image data, an embedded memory 6 for storing the compressed image data, a card controller 7, a manipulation key 8 for the user to manipulate, a display 9, and a card interface
20 10 into which an external memory card 11 can be inserted.

The external memory card 11 of the digital camera 1 is managed by the FAT file system. The external memory card 11 inserted into the card interface 10 is initialized (reformatted) for a predetermined format in accordance with

the user's formatting manipulation.

In picking up image, image data obtained from the CCD
2 is thereafter fed to the signal processor 3, the data is
given a required signal processing, and is then compressed
5 as image data for storage in the image compression
processor 5. The image data for storage is written to the
external memory card 11 with the external memory card 11
inserted into the card interface 10 under control of the
card interface 10.

10 FIG. 2 shows a procedure for setting a cluster size
when the external memory card is formatted. First in step
S1 the display 9 has shown thereon a menu panel as shown in
FIG. 6(a), to recognize selecting "reformat" of the menu
panel. In step S2 the cluster size (initial value) is read
15 out from PBR (Partition Boot Record) of the external memory
card. Next in step S3 the remaining capacity of the
external memory card is calculated corresponding to the
cluster size based on predetermined image resolution and
compression rate, thereby calculating the number of
20 pictures to be taken based on the remaining capacity.

The remaining capacity X of the external memory card
is calculated from the following mathematical expression 1
wherein the total number of sectors of the partition in the
FAT file system is TS, the number of sectors of each of the

FAT is NF, the number of directory entries in the root directory is RD, and the number of sectors per cluster (cluster size) is SP.

(Mathematical Expression 1)

$$5 \quad X = (((((TS - (NF \times 2 + RD \times 32 \div 512)) \div SP) \times SP \times 512)) \div 512) \\ - \text{the number of empty clusters} \times SP)$$

For example, the number Y of pictures to be taken is calculated from the following mathematical expression 2 when the resolution is 1024×768 pixels, and the
10 compression rate is 50%.

(Mathematical Expression 2)

$$Y = ((X \div SP) \times SP) \div (1024 \times 768 \times 0.5 \div 512)$$

Thereafter in step S4 the display 9 shows thereon the high-speed/capacity selection menu as the user graphical
15 interface as shown in FIG. 6(b). The menu includes a first display portion A for inputting priority ratio of high speed in access to the external memory card to recordable capacity by the movement of the cursor, a second display portion B for showing the cluster size (unit of used
20 capacity), a third display portion C for showing the number of pictures to be taken.

Subsequently step S5 judges whether the cursor of the first display portion moves to the high-speed side or to the capacity side by the user's manipulation, as shown in

FIG. 2. When the cursor moves to the high-speed side, step S6 follows to execute a speed-oriented setting procedure with the degree of the movement. When the cursor moves to the capacity side, step S7 follows to execute a capacity-oriented setting procedure with the degree of the movement.

As shown in FIG. 3, in the speed-oriented setting procedure an inquiry is made as to whether twice the value of the present cluster size is not greater than 64 in step S61. If the answer is affirmative, step S62 follows to set twice the value of the cluster size as a new cluster size.

Furthermore, as shown in FIG. 4, in the capacity oriented setting procedure an inquiry is made as to whether half the value of the present cluster size is not greater than 64 in step S71. If the answer is affirmative, step S72 follows to set half the value of the cluster size as a new cluster size.

For example, when the cursor shown in FIG. 6(b) moves to the high-speed side as shown by the first display portion A in FIG. 6(c), the setting of the cluster size of the second display portion B is changed from 8[sector/cluster] to 16[sector/cluster]. As a result, reduced from 100 to 70 is the number of pictures to be taken shown in the third display portion C. This enables

the user to recognize the increase of the cluster size in spite of the reduction of the number of pictures to be taken by giving priority to high speed in access.

Thereafter step S8 shown in FIG. 2 inquires whether
5 the user performs a determining manipulation in format confirmation menu shown in FIG. 6(c). When the answer is negative, the sequence returns to step S3 in FIG. 2 to recalculate and redisplay the cluster size and recalculate and redisplay the number of pictures to be taken in
10 response to resetting the priority between high speed in access and recordable capacity by the user's cursor movement.

When it is judged that the user performs the determining manipulation in step S8, step S9 follows to
15 write the cluster size shown on the second display portion to PBR of the external memory card, to thereby format the external memory card according to the written cluster size.

With the digital camera of the present invention described above, the user can confirm the cluster size and
20 the number of pictures to be taken obtained by the format of the external memory card by referring to the presentation of high-speed/capacity selecting menu shown in FIG. 6(b). The formatting can be executed so as to satisfy the user's request in high-speed in access and the number

of pictures to be taken by reinputting the priority between the high speed in access and the recordable capacity by the movement of the cursor, as shown in FIG. 6(c).

FIG. 5 shows the recording operation of a digital
5 camera comprising two interfaces for connecting two kinds
of external memory cards different in cluster size. First
in step S11, the two cluster sizes are obtained from the
two kinds of external memory cards connected to the two
interfaces, respectively. Then in step S12 an inquiry is
10 made as to whether the user manipulates the camera for
starting recording. When the inquiry is answered in the
affirmative, step S13 follows to inquire whether the size
of image file to be recorded is greater than a
predetermined value.
15 When the inquiry is answered in the affirmative, step
S14 follows to record the image file to the external memory
card having a larger cluster size. When the inquiry is
answered in the negative, step S15 follows to record the
image file to the external memory card having a smaller
20 cluster size.

With the digital camera described, one of the external
memory cards is automatically selected according to the
size of the image file to be recorded on the external
memory card, and the image file having a larger size is

recorded on the external memory card having a larger cluster size while the image file having a smaller size is recorded on the external memory card having a smaller cluster size, whereby the recording operation is realized
5 so as to strike a balance between high-speed in access and recordable capacity.

Furthermore, with digital cameras, the most suitable cluster size can be determined based on a file size calculated from the resolution and compression rate of the
10 image, and the external memory card can also be formatted for the determined cluster size. For example, it is possible that when the file size is not greater than 512 bytes, the cluster size is 1, or when the file size is not greater than 1,024 bytes, the cluster size is 2, and so on,
15 or when the file size is not greater than 32,768 bytes, the cluster size is 64.

The digital cameras of the present invention are not limited to the foregoing embodiments in construction but can be modified variously by one skilled in the art without
20 departing from the spirit of the invention as set forth in the appended claims.